



**Ecodesign Requirements for External Power Supplies
Pursuant to Directive 2009/125/IEC**

Effective date: Feb 26, 2021

Manufacturer: Motorola Solutions, Inc.
500 W Monroe Street, Ste 4400 Chicago, IL 60661-3781

EU Contact: Motorola Solutions Systems Polska Sp.z.o.o.
UI, Czerwone
Maki 82, 30-392 Krakow, Poland

Commercial Registration

Number: KRS 146875

Web:

https://www.motorolasolutions.com/en_xu/support/emea-compliance.html#phnnav_other-products

Model Identifier	Input voltage (Vac)	Input AC Frequency (Hz)	Output Voltage (Vdc)	Output Current (A)	Output Power (W)	Average Active Efficiency (%)	Efficiency at Low Load (10%)	No-load Power Consumption (W)
PS000037Axx	220-240	50/60	14	1	14	85.7-86.1	75	0.1
2571886T01	100-240	50/60	14	1.5	21	80.4-82.06	81.22	0.5
CZ083Pxx	100-240	50/60	12	0.5	6	81.35-81.61	72.06-77.70	0.075
PS000116A01	100-240	50/60	14	2.8	39.2	88.54-88.77	84.41-88.27	0.1

Model Identifier	Input voltage (Vac)	Input AC Frequency (Hz)	Output Voltage (Vdc)	Output Current (A)	Output Power (W)	Average Active Efficiency (%)	Efficiency at Low Load (10%)	No-load Power Consumption (W)
PS000150Axx	100-240	50/60	5	1.5	7.5	78.66-78.86	71.48-77.17	0.1
PS000227Axx	100-240	50/60	5	1	5	78.12-79.91	67.83-85.17	0.1
PS000277Axx	100-240	50/60	5	3	15	82.32-82.91	79.37-83.59	0.1
PS000278Axx	100-240	50/60	5/9/12	3/3/2.25	15/27/27	84.84~86.68	78.31-81.66	0.075
PS000339Axx	100-240	50/60	5	1.5	7.5	79.75-83.14	72.13-79.94	0.1
PS000228Axx	100-240	50/60	5	0.5	2.5	>73.22	>63.22	0.075 (max)
PS000212Axx	85-264	47-63	15	13.4	201	90	87.2	<0.15
PS000235A01	90-264	47-63	12	6.67	80	89	89	<0.15
PS000242Axx	90-264	47-63	15	6	90	89.5	88.6	<0.15

MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. ©2021 Motorola Solutions, Inc. All rights reserved.